

Notice



- ☐ CORRECTION ☒ PRODUCTION CHANGE
☐ SERVICE FLASH ☐ ADD INFORMATION

FILE NO.

REVISION 5

Please add this notice to the Service Manual listed below.

Category: COLOR TELEVISION	Date: June / 15 / 2007
Model: DP32647	Effective from : Chassis No. P32647-05
Destination: U.S.A. / CANADA	REF. No. SM780145

NOTE: Match the Chassis No. on the unit's back cover with the Chassis No. in the Service Manual. **If the Service Manual Chassis No. does not match the unit's**, additional Service Literature is required. This chassis is similar to Chassis No. P32647-03. Only the **difference** Service Information is given in this manual. For detailed Service Information, refer to the **Original** Service Manual and **Notices** for Chassis No. P32647-03 used in Model DP32647 (SM780145).

Servicing should be performed by only trained and qualified service personnel.

1. IN THE SERVICE ADJUSTMENTS

PAGE 4 ON-SCREEN SERVICE MENU

Item No. **088 OP2 Data** should be changed from **07h** to **0Eh** in the table and in **Note 2**.

2. IN THE CHASSIS ELECTRICAL PARTS LIST MAIN PC BOARD AND MISCELLANEOUS

The reason for change.

A : Misprint B : Quality Reliability C : Standardization
D : Design E : Add as a possible sub F : Schematic location change
G : Purchasing Request

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 10 Chassis Electrical Parts List	C1691	Old	N/A	NOT USED	0	NO	D
		New	CK1H104ZLZFNG	CERAMIC 0.1U Z 50V	1	NO	
	C1692	Old	N/A	NOT USED	0	NO	D
		New	CK1H102KLZBNG	CERAMIC 1000P K 50V	1	NO	
Page 12 Chassis Electrical Parts List	C6364 TM	Old	N/A	NOT USED	0	NO	D
		New	CEXLB1C221VDN CEXLB1C221WAN	ELECT 220U M 6.3V ELECT 220U M 6.3V	1	NO	
	C6364	Old	CEXLB0J221VDN CEXLB1C221WAN	ELECT 220U M 6.3V ELECT 220U M 6.3V	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 13 Chassis Electrical Parts List	IC1690	Old	N/A	NOT USED	0	NO	D
		New	QPST600DMT--P	IC PST6000DMT	1	NO	
	IC801	Old	QXXAAJQ0807-- QXXAVC883---M	IC LC87F4164AU IC LC874164A	1	NO	D
		New	QXXAVC644---M QXXAVC881---M	IC LC87F4164AU-Y07PDP01 IC LC874164A	1	NO	
Page 14 Chassis Electrical Parts List	L1663	Old	1AV4L2WK680MN	INDUCTOR, 68U M	1	NO	D
		New	1AV4L2WK151MN	INDUCTOR, 150U M	1	NO	
	L1671	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	L1674	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
Page 20 Chassis Electrical Parts List	R1633	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R1634	Old	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1635	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	

2. IN THE CHASSIS ELECTRICAL PARTS LIST MAIN PC BOARD AND MISCELLANEOUS

The reason for change.

A : Misprint B : Quality Reliability C : Standardization
D : Design E : Add as a possible sub F : Schematic location change
G : Purchasing Request

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 20 Chassis Electrical Parts List	R1660	Old	RGF1501FTCANL	MT GLAZE 1.5K FA 1/10W	1	NO	D
		New	RGF3300FTCANL	MT-GLAZE 330 FA 1/10W	1	NO	
	R1663	Old	N/A	NOT USED	0	NO	D
		New	RGF1801JTCANL	MT-GLAZE 1.8K JA 1/10W	1	NO	
	R1664	Old	RGF1501FTCANL	MT GLAZE 1.5K FA 1/10W	1	NO	D
		New	RGF1002FTCANL	MT-GLAZE 10K FA 1/10W	1	NO	
	R1665	Old	RGF1001FTCANL	MT GLAZE 1K FA 1/10W	1	NO	D
		New	RGF1201FTCANL	MT-GLAZE 1.2K FA 1/10W	1	NO	
	R1691	Old	N/A	NOT USED	0	NO	D
		New	RGF3302JTCANL	MT-GLAZE 33K JA 1/10W	1	NO	
	R1692	Old	N/A	NOT USED	0	NO	D
		New	RGF1202JTCANL	MT-GLAZE 12K JA 1/10W	1	NO	
	R1694	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R1696	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R1852	Old	RGF4702JTCANL	MT GLAZE 47K JA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1853	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R1858	Old	N/A	NOT USED	0	NO	D
		New	RGF4702JTCANL	MT GLAZE 47K JA 1/10W	1	NO	
	R1859	Old	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R6259	Old	N/A	NOT USED	0	NO	D
		New	RGF2701JTCANL	MT-GLAZE 2.7K JA 1/10W	1	NO	

2. IN THE CHASSIS ELECTRICAL PARTS LIST MAIN PC BOARD AND MISCELLANEOUS

The reason for change.

A : Misprint B : Quality Reliability C : Standardization
 D : Design E : Add as a possible sub F : Schematic location change
 G : Purchasing Request

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchange-ability	Reason
Page 22 Chassis Electrical Parts List	R6356	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R6376	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R6377	Old	N/A	NOT USED	0	NO	D
		New	RGF2701JTCANL	MT-GLAZE 2.7K JA 1/10W	1	NO	
	R6378	Old	N/A	NOT USED	0	NO	D
		New	RGF2701JTCANL	MT-GLAZE 2.7K JA 1/10W	1	NO	
	R818	Old	N/A	NOT USED	0	NO	D
		New	RGF1000JTCANL	MT-GLAZE 100 JA 1/10W	1	NO	
Page 23 Chassis Electrical Parts List	A001	Old	1AA0B10N222A0	ASSY, PWB, MAIN-N3HK	1	NO	D
		New	1AA0B10N222N0	ASSY, PWB, MAIN-N3HH	1	NO	
	△EL901	Old	1AV4T40B83600	LCD (V315B1-L01 REVC1/C2)	1	NO	D
		New	1AV4T40B81900	LCD (QD32HL0301-- QDI)	1	NO	

For parts or service contact

Sanyo Manufacturing Corporation
P.O. Box 2000
3333 Sanyo Road
Forrest City, Arkansas 72335-2000